



技术尺寸参数:

订货型号	连接形式		端接		尺寸(mm)				
	入口	出口	孔径		L	L1	L2	HEX	E
JBR-06MM	6mm J-LOK	6mm J-LOK	6	6	73.5	32	41.5	17	40.5
JBR-04T	1/4" J-LOK	1/4" J-LOK	6.35	6	73.5	32			
JBR-08MM	8mm J-LOK	8mm J-LOK	8	8	76.5	33			
JBR-06T	3/8" J-LOK	3/8" J-LOK	9.52	9.52	78	34	19	41.5	
JBR-10MM	10mm J-LOK	10mm J-LOK	10	10	78	34			
JBR-12MM	12mm J-LOK	12mm J-LOK	12	12	91	42	50	27	52.5
JBR-02PTF	1/8BSPTF	1/8BSPTF	12.7	12.7	91	42			
JBR-02NF	1/8NPTF	1/8NPTF	1/4	1/4	60	26	41.5	17	40.5
JBR-04PTF	1/4BSPTF	1/4BSPTF	3/8	3/8	64	28		22	43
JBR-04GF	1/4BSPPF	1/4BSPPF	1/2	1/2	76	33	50	27	52.5
JBR-02NF-02NM	1/8NPTF	1/8NPTM	1/4	1/4	60	26	41.5	17	40.5
JBR-04PTF	1/4BSPTF	1/4BSPTF	3/8	3/8	64	28		22	43
JBR-04NF-04NM	1/4NPTF	1/4NPTM	1/2	1/2	86	41	50	27	52.5
JBR-02NF-6MM	1/8NPTF	6mm J-LOK	1/4	6	66	26	41.5	17	40.5
JBR-02NF-02T	1/8NPTF	1/8" J-LOK	1/4	6.35	66	26			
JBR-02F-08MM	1/8NPTF	8mm J-LOK	1/4	8	67	26			
JBR-04NF-10MM	1/4NPTF	10mm J-LOK	3/8	10	71	28	22	43	
JBR-04NF-04T	1/4NPTF	1/4" J-LOK	3/8	9.52	71	28			
JBR-0N4F-12MM	1/4NPTF	12mm J-LOK	1/2	12	78	41	50	27	52.5
JBR-04NF-06T	1/4NPTF	3/8" J-LOK	1/2	12.7	78	41			
JBR-04PTF-04T	1/4BSPTF	1/4" J-LOK	19.05	19.05	96	45	51	38	57
JBR-04PTF-06T	1/4BSPTF	3/8" J-LOK	25.4	25.4	10	47			